

KODIAK **KD7000VR(S)** GENERATOR

KODIAK KD SERIES GENERATORS ARE DESIGNED FOR CONSTRUCTION JOBSITES OR INDUSTRIAL APPLICATIONS. DESIGNED TO BE DURABLE, DEPENDABLE AND PROVIDE STABLE POWER WHEN REQUIRED.


- 7000W
- Honda OHV with Oil Alert
- Circuit Breaker
- Full Frame Protection
- Electric Start - KD7000VRS Only
- Automatic Voltage Regulator (AVR) - System allows finer voltage control for steady output and less fluctuations.
- Large Capacity Fuel Tank with Fuel Gauge - Offers greater run-time between refueling and displays current fuel level.
- GFCI Receptacles (120V, 20A T-Slot) - Construction site approved.
- Automatic Idle Control - Lowers engine speed when power is not required. Better fuel efficiency and reduces noise.
- Silent Muffler with built in Spark Arrestor - For quieter, safe operation.
- Wheel Kit - Includes premium 10" pneumatic wheels, overall easier for portability.



Powered by
HONDA
ENGINES


	KD7000VR	KD7000VRS
Rated Output	6000W (7000W)	
Generator Type	AVR	
Engine Model	GX390	
Starting System	Recoil	Recoil/ Electric Start
AC Output	120V/240V	
Rated Amps	50.0A/25.0A	
Tank Capacity	25L	
Running Time (Rated Load, 1/2 Load)	7.6 hrs	
Noise (dB)	79	
Dimensions (in)	27.2 x 22.8 x 21.1	
Dry Weight	179lbs	185lbs

OUTLET RECEPTACLES




GFCI AC Receptacle
NEMA 5-20R
120V - 20A T-Slot

X 2



Twist Lock AC
NEMA L5-30R
120V - 30A

X 1



Twist Lock AC
NEMA L14-30R
120V/240V - 20A

X 1



MADE IN JAPAN

**Electric Start Model KD7000VRS - Battery NOT Included.