

# KODIAK KD5500VR GENERATOR


KODIAK KD SERIES GENERATORS ARE DESIGNED FOR CONSTRUCTION JOBSITES OR INDUSTRIAL APPLICATIONS. DESIGNED TO BE DURABLE, DEPENDABLE AND PROVIDE STABLE POWER WHEN REQUIRED.

- 5500W
- Honda OHV with Oil Alert
- Circuit Breaker
- Full Frame Protection
- Automatic Voltage Regulator (AVR) - System allows finer voltage control for steady output and less fluctuations.
- Large Capacity Fuel Tank with Fuel Gauge - Offers greater run-time between refueling and displays current fuel level.
- GFCI Receptacles (120V, 20A T-Slot) - Construction site approved.
- Automatic Idle Control - Lowers engine speed when power is not required. Better fuel efficiency and reduces noise.
- Silent Muffler with built in Spark Arrestor - For quieter, safe operation.
- Wheel Kit - Includes premium 10" pneumatic wheels, overall easier for portability.



Powered by  
**HONDA**  
ENGINES

	KD5500VR
Rated Output	4800W (5000W)
Generator Type	AVR
Engine Model	GX340
Starting System	Recoil
AC Output	120V/240V
Rated Amps	40.0A/20.0A
Tank Capacity	25L
Running Time (Rated Load, 1/2 Load)	8.5 hrs
Noise (dB)	78
Dimensions (in)	27.2 x 22.8 x 21.1
Dry Weight	171lbs

OUTLET RECEPTACLES		
		
GFCI AC Receptacle NEMA 5-20R 120V - 20A T-Slot	Twist Lock AC NEMA L5-30R 120V - 30A	Twist Lock AC NEMA L14-30R 120V/240V - 20A
X 2	X 1	X 1



MADE IN JAPAN